



LifeSize Phone™

Configuring the Cisco CallManager for use with LifeSize Phone™



August 2005

Copyright Notice

2005 LifeSize Communications. All rights reserved.

LifeSize Communications has made every effort to ensure that the information contained in this document is accurate and reliable, but assumes no responsibility for errors or omissions. Information in this document is subject to change without notice. Companies, names, and data used in examples herein are fictitious unless noted.

This document contains copyrighted and proprietary information, which is protected by United States copyright laws and international treaty provisions. No part of the document may be reproduced or transmitted, in any form or by any means, electronic or mechanical, for any purpose, without the express written permission from LifeSize Communications.

Trademark Acknowledgments

LifeSize™, the LifeSize logo, and LifeSize Phone™ are trademarks of LifeSize Communications. All other trademarks are the properties of their respective owners.

Third Party Notices

This software is based in part on the work of or includes trademarked technology as follows:

Cisco IOS is a registered trademark of Cisco Systems, Inc. and/or its affiliates in the US and certain other countries.

Global IP Sound, GIPS, SoundWare, NetEQ, iPCM, iLBC, GIPS VoiceEngine, and associated design marks and logos are trademarks owned or used under license by Global IP Sound AB, and may be registered in the United States and other countries. Portions copyright 1999-2004 Global IP Sound, Inc.

Portions of this software are copyright 1996-2005 RADVISION Ltd. All intellectual property rights in such portions of the Software and documentation are owned by RADVISION and are protected by United States copyright laws, other applicable copyright laws and international treaty provisions. RADVISION and its suppliers retain all rights not expressly granted.

The MIDAS package is protected by copyright 2004, 2005 Telesoft Corporation. All rights reserved.

Net SNMP is copyright by Carnegie Mellon University; The Regents of the University of California; Networks Associates Technology, Inc.; Cambridge Broadband Ltd.; Sun Microsystems, Inc.; Sparta, Inc.; Cisco, Inc. and Information Network Center of Beijing University of Posts and Telecommunications. All rights reserved.

Siren is a trademark of Polycom.

G.729 and G.723.1 standards: patented and copyright by Nokia Corporation, NEC Corporation, Universite de Sherbrooke, France Telecom, Mitsubishi Electric Corporation, and Nippon Telegraph and Telephone Corporation.

This product includes software developed by the OpenSSL Project for use in the OpenSSL Toolkit. (<http://www.openssl.org/>).

This product includes cryptographic software written by Eric Young (eyay@cryptsoft.com).

OpenSSH. Copyright (c) 1995 Tatu Ylonen <ylo@cs.hut.fi>, Espoo, Finland. All rights reserved.

Certain portions of the Software included with the system are licensed under the terms of the most recent version of the GNU General Public License ("GPL") as published by the Free Software Foundation. A copy of the GPL is available at <http://www.gnu.org/licenses/licenses.html>.

Contacting Customer Support

If you have questions, concerns, or need assistance, contact your product reseller or distributor.

Providing Customer Feedback

LifeSize Communications welcomes your comments regarding our products and services. If you have feedback about this or any LifeSize product, please send it to feedback@lifesize.com.


Contact information for LifeSize Communications is as follows:

<i>Method</i>	<i>Address</i>
Internet	http://www.lifesize.com
E-mail	support@lifesize.com
Phone	(877) LIFESIZE or (877) 543-3749 (512) 347-9300
Fax	(512) 347-9301

Configuring the Cisco CallManager for LifeSize Phone

LifeSize Phone is supported with the Cisco CallManager (CCM) version 3.x or higher. To register your LifeSize Phone with the Cisco CallManager, follow these steps.

1. Log in to the Cisco CallManager.
2. Click the **Add a Phone/Device** button.
3. Select **H.323 Client** from the list.
4. On the **Device/Phone Configuration** page, enter a device name for your LifeSize Phone (for example, *LifeSize*).
5. Enter a number for your LifeSize Phone on the CCM in the **Directory Number** field.



6. Click the **Update** button.
7. To insure that the CCM has saved the correct settings for your LifeSize Phone, review the information from the Cisco IOS command prompt as described in the following sections.

Configuring the Gateway for Your LifeSize Phone

To insure that the Cisco CallManager has saved the correct settings for your LifeSize Phone, review the following information and edit as necessary.

Access the Cisco IOS command prompt and ensure that the network interface of the gateway is configured for the LifeSize Phone to register, as shown in the following example:

```
interface GigabitEthernet0/0
h323-gateway voip interface
h323-gateway voip id gk0 ipaddr 10.10.8.1 1719 priority 1
h323-gateway voip h323-id pbx0@lifesize.com
h323-gateway voip tech-prefix 1#
h323-gateway voip bind srcaddr 10.10.8.1
!
```

Configuring the Gatekeeper on the Cisco Router

Access the command line of the Cisco router and ensure that the gatekeeper is configured for the LifeSize Phone to register, as shown in the following example:

```
gatekeeper
zone local gk0 lifesize.com
gw-type-prefix 1#* default-technology
no shutdown
!
```

Adding a Dial Plan to the Cisco CallManager

To place calls with your LifeSize Phone through the Cisco CallManager, you must first add a dial plan. You can add a plan from the CCM interface or from the Cisco command line prompt. For more information about dial plans, navigate to the following URL:






```
http://www.cisco.com/en/US/products/sw/voicesw/ps556/products\_tech\_note09186a0080094b2a.shtml
```

Once you have added a dial plan, review it from the Cisco command line prompt to ensure it is properly configured for your LifeSize Phone, as shown in the following example:


```
dial-peer voice 428 voip
answer-address 42[78].
destination-pattern 42[78].
session target ras
dtmf-relay h245-alphanumeric
codec g711ulaw
no vad
!
```

Configuring Your LifeSize Phone for CCM

You must also configure some settings on your LifeSize Phone to operate with the CCM. To ensure that you have set up your LifeSize Phone to register with the CCM, follow these steps:

1. Log in to the **Admin Menu** on your LifeSize Phone.
The **Admin Menu** provides access to advanced preferences for audio, communications, and user preferences. To access the **Admin Main Menu**, follow these steps:
 - a. Press     sequentially when the phone is idle.
 - b. Enter the default admin password 1 2 3 4 and press .
2. Press **1** on the keypad to select **Preferences**.
3. Press **2** on the keypad to select **Communications**.
4. Press **2** on the keypad to select **H.323**.
5. Set the H.323 preferences:







Menu Option	Example Value	Description
H.323 Name	LifeSize	Enter the name of the device used when making calls with the H.323 protocol.
H.323 Extension	1234	Enter the extension of the device used when making calls with the H.323 protocol.
Gatekeeper ID	gk0	Enter the ID of the H.323 gatekeeper.
Gatekeeper Mode	Manual	Select the mode the device uses to contact the H.323 gatekeeper.
Gatekeeper Hostname 1	10.10.8.1	Enter the IP address of the primary H.323 gatekeeper.
Gatekeeper Port 1	1719	Enter the IP port number of the primary H.323 gatekeeper.
Gatekeeper Hostname 2	10.10.8.1	Enter the IP address of the secondary H.323 gatekeeper.
Gatekeeper Port 2	1719	Enter the IP port number of the secondary H.323 gatekeeper.

6. Reboot your LifeSize phone.
7. Log in to the **Admin Menu** of your LifeSize Phone as described in Step 1.
8. Press **1** on the keypad to select **Preferences**.
9. Press **2** on the keypad to select **Communications**.
10. Press **2** on the keypad to select **H.323**.
11. Press the  key to scroll to page 4 of the H.323 menu options.
12. Ensure the following values have been configured:

Menu Option	Example Value	Description
Gatekeeper Status	Registered	Displays the status of the H.323 gatekeeper registration for the device.
Auto Gatekeeper Address	10.10.8.1	When Gatekeeper Mode is set to 'Auto', displays the discovered H.322 gatekeeper IP address.
Auto Gatekeeper Port	1719	When Gatekeeper Mode is set to 'Auto', displays the discovered H.322 gatekeeper IP port number.
H.235 Tunneling	Disabled	Choose Enabled to use H.235 tunneling.

Using the LifeSize Phone Keypad During Configuration

The following keys provide navigation during configuration:

Keypad Key	Function
	Toggles values, activates the cursor in a field, and accepts changes to a field.
	Behaves as up and down keys when scrolling through preferences. Volume Down also changes the text entry mode when editing a text field.
	Behaves as Back when returning to a previous screen or Backspace during text entry.
	Behaves as Cancel when changing preference values.
	Moves a selected item down in an ordered list.
	Moves a selected item up in an ordered list.

Configuration from a Web Browser

You can also configure your LifeSize Phone from a web browser by navigating to the URL displayed at the bottom of the **Admin Main Menu** on your LifeSize Phone. On the login screen, choose the language in which to display the interface, enter the admin password, and click **Submit**.

You must have Flash Player version 7 or higher installed and configured on your web browser to access the administrator configuration from a web browser. You can download the Flash Player from www.macromedia.com.

